



TECHNICAL BULLETIN

Number 4.

Revised 23/10/19

**Read in conjunction with the Manufacturers
Instructions.**

TEM Smart Switches.

This Technical Bulletin outlines differences and solutions for Installation of TEM Smart Switches.

- Wi-Fi. (Data Connection required for Advanced Functions.) or
- RF433 (Remote Switching with remote control, Advanced features not available)

Please note the differences which make Smart Switches different from mechanical switches.

- Neutral is optional.
- Smart Switches are not designed for double (or more) twisted pairs. They are a type of Automation Module and require Breakout leads from the Switch or Socket terminals.
- Use WAGO or Twisted Wire connectors for multiple connections from the breakout leads.
- Data Connection. Important if you want to use advanced functions such as Intermediate (1 or more Switching). Grouping of switches is possible with TEM Smart Switches.
- LED Back light is Blue, it cannot be turned OFF, consider placement in Bedrooms.
- Minimum Dimmer Load is 20W.

TUYA or Smart Life APP.

Use for Advanced Functions.

(Not necessary for simple Smart Touch switching).

Follow the instructions to download the APP, it's available from the Google or Apple Play Store, as a free download or use the QR Code on your Smart Phone.

Advanced Features Include:

- Association of 2 or more switches. (Intermediate)
- Grouping of Switches.
- Simple Automation IFTTT including Sunrise-Sunset , Time of Day , Schedules or other triggers.
- Voice Control with ALEXA or Google.
- Integration with some Home Automation Controllers.



TEM Australia

1300 710 974

